

Introduction to Electrical Safety

Introduction to Electrical Safety

Key concepts, hazards, preventive measures, and best practice procedures

1. Why Electrical Safety Matters

Reason	Impact
Personal injury	Shock, burns, cardiac arrest, loss of limb or life
Property damage	Fires, equipment failure, costly downtime
Legal & regulatory	OSHA, NFPA 70E, IEC 60364, local codes impose compliance
Business continuity	Reduces unplanned outages and improves productivity

2. Fundamental Electrical Terms

Term	Definition	Typical Unit
Voltage (V)	Electrical potential difference	Volts (V)
Current (I)	Flow of electric charge	Amperes (A)
Resistance (R)	Opposition to current flow	Ohms (Ω)
Power (P)	Rate of energy use	Watts (W) = V × I
Ground/earth	Reference point at zero potential, provides a path for fault current	—
Circuit breaker / fuse	Protective device that interrupts overcurrent	—

3. Common Electrical Hazards

Hazard	How it Occurs	Typical Injuries
Electric shock	Contact with live parts or voltage on the body	Burns, muscle contraction, cardiac arrest

Introduction to Electrical Safety

Hazard	How it Occurs	Typical Injuries
Arc flash	High-energy discharge between conductors	Severe burns, blindness, hearing loss
Arc blast	Pressure wave from an arc flash	Lacerations, blunt-force trauma
Electrical fire	Overloaded circuits, faulty wiring, overheating	Burns, smoke inhalation
Static discharge	Accumulated charge released to a sensitive device	Damage to electronics, ignition of flammable vapors

4. Hierarchy of Control Measures

1. **Elimination** – Remove the electrical source or task (e.g., use battery-powered tools instead of mains-powered).
 2. **Substitution** – Replace high-voltage equipment with lower-voltage alternatives.
 3. **Engineering Controls** – Install protective devices (RCDs, GFCIs, barriers, insulated enclosures).
 4. **Administrative Controls** – Develop safe work procedures, lock-out/tag-out (LOTO), training, signage.
 5. **Personal Protective Equipment (PPE)** – Insulated gloves, flame-resistant clothing, safety glasses, hearing protection, dielectric footwear.
-

5. Core Safety Practices

5.1. Lock-Out/Tag-Out (LOTO)

Step	Action
Identify	Locate all energy sources (circuit breakers, switches, disconnects).
Isolate	De-energize the equipment using the proper device.
Lock	Apply a lock that only the authorized worker can remove.
Tag	Attach a tag with the worker's name, date, and reason for shutdown.
Verify	Test the circuit (e.g., with a voltage tester) to confirm zero voltage before starting work.
Release	Remove lock & tag only after the job is complete and the system is safe to re-energize.

Introduction to Electrical Safety

5.2. Use of Test Instruments

- **Voltage detectors** – Verify presence of voltage before touching conductors.
- **Multimeters** – Measure voltage, current, resistance (always start with the highest range).
- **Clamp meters** – Measure current without breaking the circuit.
- **Insulation testers** – Check integrity